

Timespace Cartridge Station

DRIVING SECURITY



One cartridge to PC connection for all Timespace Recorders.



Dock and View

The Timespace Cartridge Station provides a quick desktop connection to a PC to review footage and GPS mapping in Timespace's PCLink software.



Playback PC software / Remote access / LiveView

| Recorder | Playback PC software | Remote access / LiveView |
|------------------------------|----------------------|--------------------------|
| X100 | PCLink100 | RemoteLink (gsm) |
| X200 | PCLink | RemoteLink |
| X300, V400, V500, X500, R500 | PCLink | PCLink |



TIMESPACE

MANUFACTURED BY **TIMESPACE** IN THE UK

DRIVING SECURITY



T705-USB Cartridge Station Installation Guide

- 1 Plug both USB connectors into PC.
- 2 Insert cartridge into cartridge station. The top of the cartridge faces forwards. (Use the labels on the cartridge station to determine the location of the disk for your model of DVR).
- 3 Windows will automatically enumerate the drive and display with a drive letter on windows explorer. This can take up to a minute.

Note: Timespace recommends the use of USB3 for optimum performance. Ensure that you are not using a combination of USB2 and USB3 on your PC, as this will prevent the Cartridge Station from functioning.

Single USB cable operation

- If your PC has only one USB socket available, plug in the USB socket labelled 'X200' for X200 or X100 hard disks (wide connector). If using an X300, V400 or V500 cartridge then plug in the other USB cable. Note that if the disk is not detected by windows and is under-powered (can make a faint clicking noise) both USB cables must be used as two cables provides more power. Timespace recommend where possible the use of both cables.
- LED on the front of the cartridge station is green when cartridge station is powered and flickers red during data transfer (X300/V400/V500 carts only).
- Windows XP, Vista, 7, 8, 10 compatible. Older versions of windows may be used with the appropriate drivers installed.

Trouble-shooting – my cartridge is not detected by Windows

- Make sure cartridge is correct way round and pushed home.
- Make sure for X100/X200 cartridges that the cartridge is switched on.
- The disk enumeration (to get a drive letter) can take up to a minute – please be patient.
- Use both USB plugs (disk may require more power).
- Check disk status using disk manager – use universal command **compmgmt.msc** to check disk status. If the disk appears here but is not creating a drive letter, it may be formatted incorrectly – contact Timespace for assistance.

Cartridge to Playback PC Cable

| Recorder | Part No. | Description |
|---------------|----------|----------------------------------|
| X300 | T605-USB | PCLink Suite + USB Cable |
| V400, V500 | T605-USB | PCLink Suite + USB Cable |
| All recorders | T705-USB | PCLink Suite + Cartridge Station |

Including X100 and X200

Technical Details

| | |
|------------------|---|
| Protocol | X100 and X200 – USB2 X300, V400, V500, X500 – USB3 |
| PC Connection | Twin USB connectors |
| USB Cable length | 1 m |
| Status | LED – Green power, Amber active |
| Enclosure | ABS |
| Dimensions (mm) | 150mm diameter x 90mm high |
| Weight | 0.6 Kg |
| IP rating | IP40 |

Regulatory Approvals

CE Mark (EN55032:2012, EN55024:2010)

VCA CoP approval

RoHS

WEEE

Please note:

- The purchase of USB Kits T505-USB, T605-USB or Cartridge Station T705-USB includes the necessary license for the use of PCLink Suite software, including free of charge updates, on a single PC (reasonable use policy allows installation on a secondary portable PC / laptop). Timespace Technology does not authorise the unlicensed usage of PCLink Suite software.
- USB kit cables are not available separately.

Timespace Technology Ltd reserves the right to amend product specifications without notice and without incurring obligation.



TIMESPACE

Timespace Technology Ltd Lakeview Court Ermine Business Park Huntingdon PE29 6UA UK

t: +44 (0)1480 414147 f: +44 (0)1480 414146 e: mail@tspace.co.uk www.tspace.co.uk



FM 525394